



AA-ML

Optional Mic/Line Input Module for Atlas Sound
AA Series Model AA120M Mixer Amplifier



Applications

The AA-ML is an accessory input module for the AA120M. When inserted into the AA120M it can be used as an additional Line or Mic input. Unit features a level control, RCA style summing jacks for unbalanced line level signals, Phoenix style input for mic level signals with switchable 18V phantom power supply, remote VCA level control and 6 dB/octave high pass filter (-3 dB @ 300 Hz). Note: HPF is only functional for Mic input.

Technical Specifications

| | |
|--------------------------|-----------------------------------|
| Microphone Input: | 600 Ω Balanced |
| Sensitivity: | 3mV |
| Line Input: | 10K Ω Unbalanced |
| Sensitivity: | 300mV |
| Microphone/Line Switch: | (PCB Jumper) |
| Mic Input Phantom Power: | +18V (PCB Jumper) |
| Mic Low-Cut Filter: | -10 dB at 100 Hz (PCB Jumper) |
| Output Level Control: | Front Panel Screwdriver Adjust |
| Remote Volume Control: | 10K Pot |
| Terminations: | Mic Input = Phoenix terminals |
| | Remote Volume = Phoenix terminals |
| | Line/AUX = Dual RCA Summing Jacks |

